

## 500mW SOD-123 Fast Switching Diode

### Features

- 4.0nS; Fast switching device (TRR <4.0 nS)
- 500mW; power dissipation of 500mW
- High stability and high reliability
- Low reverse leakage



RoHS  
COMPLIANT



Marking: T5 SOD-123

### Mechanical Data

- SOD-123 Small outline plastic package
- Polarity: color band denotes cathode end
- Epoxy UL: 94V-0
- Mounting position: any

### Maximum Ratings & Thermal Characteristics (T<sub>A</sub> =25°C unless otherwise noted)

Parameters	Symbol	Value	Unit
Reverse voltage	V <sub>R</sub>	75	V
Peak reverse voltage	V <sub>RM</sub>	100	V
Power dissipation	P <sub>D</sub>	500	mW
Operating junction temperature	T <sub>J</sub>	150	°C
Storage temperature range	T <sub>S</sub>	-55-+150	°C
Working Inverse voltage	W <sub>IV</sub>	75	V
Average rectified current	I <sub>O</sub>	200	mA
Non-repetitive peak forward current	I <sub>FM</sub>	500	mA
Peak forward surge current @tp=1us; TA=25 °C	I <sub>FSM</sub>	2.0	A





Valid provided that electrodes are kept at ambient temperature.

### Electrical Characteristics (T<sub>A</sub> =25°C unless otherwise noted)

Parameter	Symbols	Test Condition	Limits		Unit
			Min	Max	
Breakdown Voltage	BV	IR=100uA	100		V
		IR=5uA	75		
Reverse Leakage Current	IR	VR=20V		25	nA
		VR=75V		2.5	uA
Forward Voltage	VF	IF=5mA	0.62	0.72	V
		IF=10mA		0.855	
		IF=100mA		1.00	
		IF=150mA		1.25	
Reverse Recovery Time	TRR	IF = 10ma IR= 10mA, Irr=0.1mA		4	nS
		RL=100Ω			
Capacitance	Cj	VR=0V, f=1MHZ		4	pF


## Ratings and Characteristics Curves

( $T_A = 25^\circ\text{C}$  unless otherwise noted)



## Package Outline Dimensions

in inches (millimeters)



SYMBOL	DIMENSIONS	
	MIN.	MAX.
A	1.050	1.250
A1	0.000	0.100
A2	1.050	1.150
b	0.450	0.650
c	0.080	0.150
D	1.500	1.700
E	2.600	2.800
E1	3.550	3.850
L	0.500REF	
L1	0.250	0.450
$\theta$	0°	8°

## Revision History

Document Version	Date of release	Description of changes
Rev.A	2014.04.01	First issue

## **Disclaimers**

These materials are intended as a reference to assist our customers in the selection of the Suzhou Good-Ark product best suited to the customer's application; they do not convey any license under any intellectual property rights, or any other rights, belonging to Suzhou Good-Ark Electronics Co., Ltd. or a third party.

Suzhou Good-Ark Electronics Co., Ltd. assumes no responsibility for any damage, or infringement of any third-party's rights, originating in the use of any product data, diagrams, charts, programs, algorithms, or circuit application examples contained in these materials.

All information contained in these materials, including product data, diagrams, charts, programs and algorithms represents information on products at the time of publication of these materials, and are subject to change by Suzhou Good-Ark Electronics Co., Ltd. without notice due to product improvements or other reasons. It is therefore recommended that customers contact Suzhou Good-Ark Electronics Co., Ltd. or an authorized Suzhou Good-Ark Electronics Co., Ltd. for the latest product information before purchasing a product listed herein. The information described here may contain technical inaccuracies or typographical errors. Suzhou Good-Ark Electronics Co., Ltd. assumes no responsibility for any damage, liability, or other loss rising from these inaccuracies or errors. Please also pay attention to information published by Suzhou Good-Ark Electronics Co., Ltd. by various means, including our website home page.

(<http://www.goodark.com>)

When using any or all of the information contained in these materials, including product data, diagrams, charts, programs, and algorithms, Please be sure to evaluate all information as a total system before making a final decision on the applicability of the information and products. Suzhou Good-Ark Electronics Co., Ltd. assumes no responsibility for any damage, liability or other loss resulting from the information contained herein.

The prior written approval of Suzhou Good-Ark Electronics Co., Ltd. is necessary to reprint or reproduce in whole or in part these materials.

Please contact Suzhou Good-Ark Electronics Co., Ltd. or an authorized distributor for further details on these materials or the products contained herein.