

**GOOD-ARKElectronics** 

## SOD- 123 Plastic-Encapsulate Schottky Barrier Diode

#### **Features**

• High Current Capability

• Low Forward Voltage Drop

#### **Mechanical Data**

SOD-123 Small Outline Plastic PackagePolarity: Color band denotes cathode end

• Epoxy UL: 94V-0

• Mounting Position: Any





Marking:

SOD-123

B0520W: SD B0530W: SE B0540W: SF

Maximum Ratings & Thermal Characteristics (T <sub>A</sub> =25°C unless otherwise noted)					
Parameters	Symbol		Unit		
		B0520W	B0530W	B0540W	
Maximum repetitive peak reverse voltage	$V_{RRM}$	20	30	40	V
Maximum RMS voltage	V <sub>RMS</sub>	14	21	28	V
Maximum DC blocking voltage	$V_{DC}$	20	30	40	٧
Non-repetitive Peak Forward Current	I <sub>FM</sub>	0.5			Α
Peak forward surge current 8.3 ms single half sine-wave	I <sub>FSM</sub>	5.5		Α	
Power dissipation	P <sub>D</sub>	500		mW	
Typical thermal resistance	$R_{\theta JA}$	200		°C/W	
Storage temperature range	T <sub>STG</sub>	-50-+150		$^{\circ}$	
Voltage rate of change	D <sub>v/dt</sub>	1000			V/uS


Electrical Characteristics (T <sub>A</sub> =25°C unless otherwise noted)						
Parameter	Symbols	Test Condition		Limits		
			B0520W	B0530W	B0540W	Unit
Maximum reverse breakdown voltage	VD	IR=250uA	20			
	VR	IR=200uA		30		V
		IR=20uA			40	
Maximum reverse current	In	VR=10V	75			
	IR	VR=15V		20		
		VR=20V	250		10	uA
		VR=30V		130		
		VR=40V			20	
Maximum forward voltage	VF	IF=0.1A	0.330	0.375		
		IF=0.5A	0.385	0.430	0.510	V
		IF=1.0A			0.620	
Capacitance between terminals	Cl	VR=0V, f=1MHZ			170	pF


# B0520W-B0530W-B0540W


GOOD-ARKElectronics


#### **Ratings and Characteristics Curves**

(TA = 25°C unless otherwise noted)











# B0520W/B0530W/B0540W GOOD-ARKElectronics


### **Package Outline Dimensions**

in inches (millimeters)





CVMDDI	DIMENSIONS			
SYMBOL	MIN.	MAX.		
Α	1.050	1.250		
A1	0.000	0.100		
A2	1.050	1.150		
b	0.450	0.650		
$\subset$	0.080	0.150		
D	1.500	1.700		
E	2,600	2,800		
E1	3,550	3,850		
L	0.500REF			
L1	0.250	0.450		
θ	0*	8*		



### **Revision History**

Document Version	Date of release	Description of changes
Rev.A	2020.03.31	First issue

# GOOD-ARK

#### B0520W-B0530W-B0540W

GOOD-ARKElectronics

#### **Disclaimers**

These materials are intended as a reference to assist our customers in the selection of the Suzhou Good-Ark product best suited to the customer's application; they do not convey any license under any intellectual property rights, or any other rights, belonging to Suzhou Good-Ark Electronics Co., Ltd.or a third party.

Suzhou Good-Ark Electronics Co., Ltd. assumes no responsibility for any damage, or infringement of any third-party's rights, originating in the use of any product data, diagrams, charts, programs, algorithms, or circuit application examples contained in these materials.

All information contained in these materials, including product data, diagrams, charts, programs and algorithms represents information on products at the time of publication of these materials, and are subject to change by Suzhou Good-Ark Electronics Co., Ltd. without notice due to product improvements or other reasons. It is therefore recommended that customers contact Suzhou Good-Ark Electronics Co., Ltd. or an authorized Suzhou Good-Ark Electronics Co., Ltd. for the latest product information before purchasing a product listed herein. The information described here may contain technical inaccuracies or typographical errors. Suzhou Good-Ark Electronics Co., Ltd. assumes no responsibility for any damage, liability, or other loss rising from these inaccuracies or errors. Please also pay attention to information published by Suzhou Good-Ark Electronics Co., Ltd. by various means, including our website home page. (http://www.goodark.com)

When using any or all of the information contained in these materials, including product data, diagrams, charts, programs, and algorithms, Please be sure to evaluate all information as a total system before making a final decision on the applicability of the information and products. Suzhou Good-Ark Electronics Co., Ltd. assumes no responsibility for any damage, liability or other loss resulting from the information contained herein.

The prior written approval of Suzhou Good-Ark Electronics Co., Ltd. is necessary to reprint or reproduce in whole or in part these materials.

Please contact Suzhou Good-Ark Electronics Co., Ltd. or an authorized distributor for further details on these materials or the products contained herein.