

2.5A,50-1000V Fast Recovery Rectifiers

Features

- Low leakage current
- Low forward voltage drop
- Glass passivated chip junction
- For general purpose applications
- Moisture sensitivity: level 1, per J-STD-020
- For fast switching and low logic level applications
- High temperature soldering guaranteed: 260°C/10 seconds



Applications

• Small battery charger, Power supplies

Maximum Ratings & Electrical Characteristics(TA=25°C unless otherwise noted)											
Parameter	Symbol	FR251	FR252	FR253	FR254	FR255	FR255 -STR	FR256	FR257	FR257 -STR	Unit
Maximum repetitive peak reverse voltage	Vrrm	50	100	200	400	600	600	800	1000	1000	V
Maximum RMS voltage	V _{RMS}	35	70	140	280	420	420	560	700	700	V
Maximum DC blocking voltage	V _{DC}	50	100	200	400	600	600	800	1000	1000	V
Maximum average forward rectified current	lf(AV)		2.5							А	
Peak forward surge current,8.3ms single half sine-wave superimposed on rated load per diode	IFSM		125						A		
Operating junction temperature range	TJ		-55 to +135						°C		
Storage temperature range	T _{STG}		-55 to +150						°C		

Thermal-Mechanical Specifications (TA=25°C unless otherwise noted)						
Parameter	Symbol	Тур	Unit			
Thermal Resistance, Junction to Ambient	Reja	62	°C /W			
Thermal Resistance, Junction to Case	R _{θJC}	28	°C /W			
Thermal Resistance, Junction to Lead	R _{ejL}	19	°C /W			



Electrical Specifications(TA=25°C unless otherwise noted)												
Parameter	Symbol	Test Conditions	FR251	FR252	FR253	FR254	FR255	FR255 -STR	FR256	FR257	FR257 -STR	Unit
Forward Drop Voltage	VF	I⊧=2.5A					1.30					V
Reverse	1-	TJ =25℃		5							uA	
leakage current @V _R	IR	T」=125℃	100								uA	
Typical junction capacitance	CJ	4.0 V 1 MHZ	55				pF					
Maximum reverse	trr	I _F =0.5A, I _R =1.0A,		1;	50		250	150	5(00	250	nS
recovery time		I _{RR} =0.25A										


Note:


1. Valid provided that leads at a distance of 9.5 mm from case are kept at ambient temperature.





Ratings and Characteristics Curves

(TA = 25°C unless otherwise noted)















FIG.4-TYPICAL JUNCTION CAPACITANCE










Package Outline Dimensions

in inches (millimeters)

R-3



Dimensions in inches and (millimeters)

Revision History

Document Version	Date of release	Description of changes
Rev.A	2021.06.01	Released Datasheet
Rev.B	2024.02.28	Modify document format



Disclaimers

These materials are intended as a reference to assist our customers in the selection of the Suzhou Good-Ark product best suited to the customer's application; they do not convey any license under any intellectual property rights, or any other rights, belonging to Suzhou Good-Ark Electronics Co., Ltd.or a third party.

Suzhou Good-Ark Electronics Co., Ltd. assumes no responsibility for any damage, or infringement of any thirdparty's rights, originating in the use of any product data, diagrams, charts, programs, algorithms, or circuit application examples contained in these materials.

All information contained in these materials, including product data, diagrams, charts, programs and algorithms represents information on products at the time of publication of these materials, and are subject to change by Suzhou Good-Ark Electronics Co., Ltd. without notice due to product improvements or other reasons. It is therefore recommended that customers contact Suzhou Good-Ark Electronics Co., Ltd. or an authorized Suzhou Good-Ark Electronics Co., Ltd. for the latest product information before purchasing a product listed herein. The information described here may contain technical inaccuracies or typographical errors. Suzhou Good-Ark Electronics Co., Ltd. assumes no responsibility for any damage, liability, or other loss rising from these inaccuracies or errors. Please also pay attention to information published by Suzhou Good-Ark Electronics Co., Ltd. by various means, including our website home page. (http://www.goodark.com)

When using any or all of the information contained in these materials, including product data, diagrams, charts, programs, and algorithms, Please be sure to evaluate all information as a total system before making a final decision on the applicability of the information and products. Suzhou Good-Ark Electronics Co., Ltd. assumes no responsibility for any damage, liability or other loss resulting from the information contained herein.

The prior written approval of Suzhou Good-Ark Electronics Co., Ltd. is necessary to reprint or reproduce in whole or in part these materials.

Please contact Suzhou Good-Ark Electronics Co., Ltd. or an authorized distributor for further details on these materials or the products contained herein.