

# **3A,60V Schottky Barrier Rectifier**

### **Features**

- Low leakage current
- Schottky barrier diode
- Low forward voltage drop
- Moisture sensitivity: level 1, per J-STD-020
- Halogen-free according to IEC 61249-2-21 definition
- High temperature soldering guaranteed: 260 ℃/10 seconds



eSGB (DO-221AC)

### **Applications**

For use in low voltage, high frequency inverters, free-wheeling and polarity protection application.

Maximum Ratings & Electrical Characteristics(TA=25°C unless otherwise noted)					
Parameter	Symbol	LSL36	Unit		
Maximum repetitive peak reverse voltage	V <sub>RRM</sub>	60	V		
Maximum RMS voltage	V <sub>RMS</sub>	42	V		
Maximum DC blocking voltage	V <sub>DC</sub>	60	V		
Maximum average forward rectified current	l <sub>F(AV)</sub>	3	А		
Peak forward surge current,8.3ms single half sine-wave superimposed on rated load per diode	IFSM	100	А		
Operating junction temperature range	TJ	-55 to +125	°C		
Storage temperature range	Тѕтс	-55 to +125	°C		

Thermal-Mechanical Specifications (TA=25°C unless otherwise noted)					
Parameter	Symbol	Тур	Unit		
Thermal Resistance, Junction to Ambient	Reja	85	°C /W		
Thermal Resistance, Junction to Case	Rejc	15	°C /W		
Thermal Resistance, Junction to Lead	R <sub>θJL</sub>	18	°C /W		



# GOOD-ARK Electronics

Electrical Specifications(TA=25°C unless otherwise noted)							
Parameter	Symbol	Test Conditions	Тур	Max	Unit		
Forward Drop Voltage	VF	I⊧=1A T <sub>A</sub> =25℃	0.42	0.45	V		
		I <sub>F</sub> =2A T <sub>A</sub> =25℃	0.47	0.50			
		I⊧=3A T <sub>A</sub> =25℃	0.51	0.55			
		I <sub>F</sub> =3A T <sub>A</sub> =100℃	0.46	-			
Reverse leakage current @V <sub>R</sub>	I <sub>R</sub>	T <sub>J</sub> =25°C	5		A		
		T <sub>J</sub> =100°C	100		- mA		
Typical junction capacitance	Сл	4.0 V 1 MHZ	1320		pF		

#### Note:

1. Mounted on copper pad area of 0.2x0.2" (5.0 x 5.0mm) to each terminal.





### **Ratings and Characteristics Curves**

(TA = 25°C unless otherwise noted)




Figure 1. Forward Current Derating Curve




Figure 3. Typical Reverse Characteristics




Figure 5. Typical Instantaneous Forward Characteristics




Figure 2.Maximum Non-Repetitive Peak Forward Surge Current





Figure 4. Typical Junction Capacitance



## **Package Outline Dimensions**


in inches (millimeters)


# eSGB (DO-221AC)












Soldering footprint



## **Revision History**

Document Version	Date of release	Description of changes
Rev.A	2021.06.01	Released Datasheet
Rev.B	2023.10.12	Modify document format
Rev.C	2023.12.29	Modify package name





#### **Disclaimers**

These materials are intended as a reference to assist our customers in the selection of the Suzhou Good-Ark product best suited to the customer's application; they do not convey any license under any intellectual property rights, or any other rights, belonging to Suzhou Good-Ark Electronics Co., Ltd.or a third party.

Suzhou Good-Ark Electronics Co., Ltd. assumes no responsibility for any damage, or infringement of any third-party's rights, originating in the use of any product data, diagrams, charts, programs, algorithms, or circuit application examples contained in these materials.

All information contained in these materials, including product data, diagrams, charts, programs and algorithms represents information on products at the time of publication of these materials, and are subject to change by Suzhou Good-Ark Electronics Co., Ltd. without notice due to product improvements or other reasons. It is therefore recommended that customers contact Suzhou Good-Ark Electronics Co., Ltd. or an authorized Suzhou Good-Ark Electronics Co., Ltd. for the latest product information before purchasing a product listed herein. The information described here may contain technical inaccuracies or typographical errors. Suzhou Good-Ark Electronics Co., Ltd. assumes no responsibility for any damage, liability, or other loss rising from these inaccuracies or errors. Please also pay attention to information published by Suzhou Good-Ark Electronics Co., Ltd. by various means, including our website home page. (http://www.goodark.com)

When using any or all of the information contained in these materials, including product data, diagrams, charts, programs, and algorithms, Please be sure to evaluate all information as a total system before making a final decision on the applicability of the information and products. Suzhou Good-Ark Electronics Co., Ltd. assumes no responsibility for any damage, liability or other loss resulting from the information contained herein.

The prior written approval of Suzhou Good-Ark Electronics Co., Ltd. is necessary to reprint or reproduce in whole or in part these materials.

Please contact Suzhou Good-Ark Electronics Co., Ltd. or an authorized distributor for further details on these materials or the products contained herein.