

10A,120V Schottky Barrier Rectifier

Features

- Low leakage current
- Schottky barrier diode
- Low forward voltage drop
- Very low profile typical height of 1.1 mm
- Moisture sensitivity: level 1, per J-STD-020
- Halogen-free according to IEC 61249-2-21 definition
- High temperature soldering guaranteed: 260°C/10 seconds



Applications

For use of fast switching in RF module, lighting, cellular phone, portable device, power supplies and other consumer applications.

Maximum Ratings & Electrical Characteristics(TA=25°C unless otherwise noted)				
Parameter	Symbol	SGC101B2S	Unit	
Maximum repetitive peak reverse voltage	Vrrm	120	V	
Maximum RMS voltage	VRMS	84	V	
Maximum DC blocking voltage	V _{DC}	120	V	
Maximum average forward rectified current	lf(AV)	10	А	
Peak forward surge current,8.3ms single half sine-wave superimposed on rated load per diode	I _{FSM}	175	A	
Operating junction temperature range	TJ	-55 to +150	°C	
Storage temperature range	Тѕтс	-55 to +150	°C	

Thermal-Mechanical Specifications (TA=25°C unless otherwise noted)				
Parameter	Symbol	Тур	Unit	
Thermal Resistance, Junction to Ambient	Reja	40	°C /W	
Thermal Resistance, Junction to Case	Rejc	15	°C /W	
Thermal Resistance, Junction to Lead	Rejl	7	°C /W	



Electrical Specifications(TA=25°C unless otherwise noted)						
Parameter	Symbol	Test Conditions		Тур	Мах	Unit
Forward drop voltage	Vf	I _F =1A	− T _A =25℃	0.40	0.45	V
		I _F =2A		0.44	0.49	
		I _F =5A		0.54	0.60	
		I _F =10A		0.68	0.75	
		I _F =1A	- T _A =125℃	0.29	-	
		I _F =2A		0.36	-	
		I⊧=5A		0.48	-	
		I _F =10A		0.57	-	
Reverse leakage current @V _R	I _R	T _J =25°C		0.015	0.2	mA
		TJ=125℃		10.4	30	
Typical junction capacitance	CJ	4.0V 1 MHZ		975		pF

Note:

1. Mounted on copper pad area of 30 x 30mm to each terminal.



SGC101B2S GOOD-ARK Electronics

Ratings and Characteristics Curves




Figure 1.Forward Current Derating Curve




Figure 3. Typical Reverse Characteristics




Figure 5. Typical Junction Capacitance




Figure 2.Maximum Non-Repetitive Peak Forward Surge Current





Figure 4. Typical Instantaneous Forward Characteristics




Package Outline Dimensions


in inches (millimeters)

eSGC (TO-277B)





			_		
DIM	Unit:	mm	Unit: inch		
	MIN	MAX	MIN	MAX	
HE	6.4	6.6	0.252	0.260	
E	5.6	5.8	0.220	0.228	
D	4.1	4.3	0.161	0.169	
B1	1.7	1.9	0.067	0.075	
B2	0.8	1	0.031	0.039	
Α	1.05	1.2	0.041	0.047	
С	0.3	0.4	0.012	0.016	
L	0.85	1.1	0.033	0.043	
L1	4.2	4.4	0.165	0.173	
L2	3.52 Typ.		0.139	Э Тур.	
L3	1.1	1.4	0.043	0.055	
D1	3	3.3	0.118	0.130	
E1	1.86 Typ.		0.073	3 Тур.	



Revision History

Document Version	Date of release	Description of changes
Rev.A	2021.06.01	Released Datasheet
Rev.B	2023.10.11	Modify document format
Rev.C	2023.12.29	Modify package name



Disclaimers

These materials are intended as a reference to assist our customers in the selection of the Suzhou Good-Ark product best suited to the customer's application; they do not convey any license under any intellectual property rights, or any other rights, belonging to Suzhou Good-Ark Electronics Co., Ltd.or a third party.

Suzhou Good-Ark Electronics Co., Ltd. assumes no responsibility for any damage, or infringement of any thirdparty's rights, originating in the use of any product data, diagrams, charts, programs, algorithms, or circuit application examples contained in these materials.

All information contained in these materials, including product data, diagrams, charts, programs and algorithms represents information on products at the time of publication of these materials, and are subject to change by Suzhou Good-Ark Electronics Co., Ltd. without notice due to product improvements or other reasons. It is therefore recommended that customers contact Suzhou Good-Ark Electronics Co., Ltd. or an authorized Suzhou Good-Ark Electronics Co., Ltd. for the latest product information before purchasing a product listed herein. The information described here may contain technical inaccuracies or typographical errors. Suzhou Good-Ark Electronics Co., Ltd. assumes no responsibility for any damage, liability, or other loss rising from these inaccuracies or errors. Please also pay attention to information published by Suzhou Good-Ark Electronics Co., Ltd. by various means, including our website home page. (http://www.goodark.com)

When using any or all of the information contained in these materials, including product data, diagrams, charts, programs, and algorithms, Please be sure to evaluate all information as a total system before making a final decision on the applicability of the information and products. Suzhou Good-Ark Electronics Co., Ltd. assumes no responsibility for any damage, liability or other loss resulting from the information contained herein.

The prior written approval of Suzhou Good-Ark Electronics Co., Ltd. is necessary to reprint or reproduce in whole or in part these materials.

Please contact Suzhou Good-Ark Electronics Co., Ltd. or an authorized distributor for further details on these materials or the products contained herein.